

Tabla de potencia y corriente de motores

Potencia		230V			Potencia		400V		
KW	HP	Consumo AMPERES	Cable Rec. MM2	Int.Prot.Lineo AMP.	KW	HP	Consumo AMPERES	Cable Rec. MM2	Int.Prot.Lineo AMP.
0.37	0.5	1.9	1.50	6	0.37	0.5	1.1	1.50	6
0.55	0.75	2.6	1.50	6	0.55	0.75	1.5	1.50	6
0.75	1	3.3	1.50	10	0.75	1	1.9	1.50	6
1.1	1.5	4.7	1.50	10	1.1	1.5	2.7	1.50	6
1.5	2	6.3	1.50	16	1.5	2	3.6	1.50	10
2.2	3	8.5	1.50	20	2.2	3	4.9	1.50	10
3	4	11.3	2.50	20	3	4	6.5	1.50	16
3.7	5	14.2	4.00	32	3.7	5	8.1	1.50	20
4	5.5	15	4.00	32	4	5.5	8.5	1.50	20
5.5	7.5	20	6.00	50	5.5	7.5	11.5	2.50	32
7.5	10	27	10.00	63	7.5	10	15.5	4.00	32
11	15	38	16.00	63	11	15	22	6.00	50
15	20	51	25.00	100	15	20	29	10.00	63
18.5	25	61	25.00	100	18.5	25	35	10.00	63
22	30	72	30.00	150	22	30	41	16.00	63

Notas:

- La corriente se toma en base a motores trifásicos 4 polos 1500 rpm.
- El interruptor recomendado protege la línea, no protege al motor.